

microlifewww.microlife.com
Pulse Oximeter
Serial number: 13979
Microlife AG**Pulse Oximeter**

- EN**
- 1. ON/OFF button
 - 2. Oxygen saturation (value as percentage)
 - 3. Pulse rate (value in beats per minute)
 - 4. Pulse wave (plethysmographic wave)
 - 5. Pulse bar
 - 6. Low battery indicator
 - 7. Inserting the batteries
 - 8. Attaching the lanyard
 - 9. Display modes
 - 10. Operation principle

Dear Customer,
This Microlife finger pulse oximeter is a portable non-invasive device intended for spot-checking of the oxygen saturation of arterial hemoglobin (SpO_2) and pulse rate of adult and pediatric patients. It is suitable for private use (at home or on the go) as well as for use in the medical sector (hospitals, hospital-like facilities). It has been clinically proven to be of high precision during repeatability.

If you have any questions, problems or want to order spare parts please contact your local Microlife-Customer Service. You can find the address of our service center in the address of the Microlife dealer in your country. Alternatively, visit the internet at www.microlife.com, where you will find a wealth of invaluable information on our products.

Retain instructions in a safe place for future reference. Stay healthy - Microlife AG!

1. Explanation of Symbols

Batteries and electronic devices must be disposed of in accordance with the locally applicable regulations, not with domestic waste.

Read the instructions carefully before using this device.

2. Inserting the batteries

After you have unpacked your device, first insert the batteries. The battery compartment is on the bottom of the device. Remove the battery cover by sliding it in the direction shown. Insert two AAA batteries (2 x 1.5 V, size AAA), thereby closing the indicated position.

Replace the batteries when the low power indicator (●) appears on the display.

3. Adjusting Display Mode and Brightness**Display Mode**

When the device is switched on, shortly press the ON/OFF button (●) to switch to another display mode to select your desired display mode (●). There are 6 different display modes. The default setting is mode 1.

Brightness

Hold down the ON/OFF button (●) for longer than one second to adjust the brightness of the device. The display will show $\text{Br} +10$. There are 10 levels of brightness. The default setting is level 4.

4. Using the Lanyard

1. Thread the lanyard through the hanging hole at the rear of the device.
2. Thread the thicker end of the lanyard through the threaded end before pulling it tightly.

5. Malfunctions and Actions to take**Description Symptom/Possible causes Solutions****PR bpm** Pulse rate (value in beats per minute)

Operating conditions:
 $5 - 40^\circ\text{C} / 41 - 104^\circ\text{F}$
Storage conditions:
 $-20 - +55^\circ\text{C} / -4 - +131^\circ\text{F}$

CE 0123 CE Marking of Conformity**2. Important Safety Instructions**

• Follow instructions for use. This document provides important product safety and safety information regarding this device. Please read the instructions before using the device and keep for future reference.

• This device may only be used for the purposes described in these instructions. The manufacturer does not accept responsibility for damage caused by incorrect application.

• Never immerse this device in water or other liquids. For cleaning please follow the instructions in the «Cleaning and Disinfecting» section.

• Do not use this device if you think it is damaged or not working correctly.

• Never open this device.

• This device comprises sensitive components and must be treated with care. Observe the storage and operating conditions described in the «Technical Specifications» section.

• Protect it from:

- water and moisture

- extreme temperatures

- impact and dropping

- direct sunlight and dust

- heat and cold

• The function of this device may be compromised when used close to strong electromagnetic fields such as mobile phones or radio installations and we recommend a distance of at least 15 cm (according to IEC 60611-1-2 table 5). In cases where this is not possible, please verify if the device is working properly before use.

• Do not use the device in an MRI or CT environment.

• This device is not intended for continuous monitoring.

• This device does not have an alarm function and is therefore not suitable for evaluating medical results. Do not use the device for medical purposes.

• Do not sterilize this device using autoclaving or ethylene oxide sterilization. This device is not intended for sterilization.

• If the device is not going to be used for a prolonged period of time, ensure that it is stored correctly.

• Ensure that children do not use this device unsupervised; some parts are small enough to be swallowed. Be aware of the risk of strangulation in this case this device is supplied with cables or tubes.

• Use of this device is not intended as a substitute for a consultation with your doctor.

3. General Description

Oxygen saturation indicates the percentage of hemoglobin in arterial blood that is loaded with oxygen. This is a very important parameter for respiratory circulation system. Many respiratory diseases can result in lower oxygen saturation in human blood.

Following formula defines oxygen saturation: Automatic regulation of oxygen dysfunction caused by anaesthesia, intensive postoperative trauma, injuries caused by some medical examinations. These situations may result in light-headedness, asthma and vomiting. Therefore, it is very important to know the oxygen saturation of a patient so that doctors can detect problems in a timely manner.

4. Measurement Principles

Principle of this finger pulse oximeter: A mathematical formula is established making use of Lambert-Beer law according to which the absorption characteristics of deoxygenated hemoglobin (Hb) and oxyhemoglobin (SpO_2) in red and near-infrared zones.

Operation principle of this device: Photoelectric oxymeter inspection technology is adopted. According to this principle, the device uses a light source emitting a beam of light with a wavelength of 660 nm (red) and 905 nm (near infrared) to illuminate the skin of the finger. The height of the difference wavelength of lights (660 nm red and 905 nm near infrared light) can be focused onto a human finger through a clamping finger-type sensor. A measured signal obtained by a photosensitive element, will be shown on the display through processing of the signal by a microprocessor.

Diagram of Operation Principle (1):
1. Red and infrared-ray emission tube.
2. Red and infrared-ray receipt tube.

5. Directions for Use

1. Insert the batteries as described in the «Inserting the batteries» (●) section.

2. Insert one finger (nail side up, index or middle finger is recommended) into the finger opening of the device. Be sure to fully insert the finger so that the sensors are completely covered by the finger.

3. Retain the device allowing it to clamp down on the finger.

4. Press the ON/OFF button (●) to turn the device on.

5. Do not shake your finger during the measurement. It is recommended that you do not move your body whilst taking a reading.

Technical alterations reserved.

Specialist Dealer / Představatel / Специализованный дилер / Specialized distributor / Distributor de specialitate / Specializovaný dealer / Specializovaný predajca / Ovlaščený diler / Forgalmazó / Офис продажи

Beijing Choice Electronic Technology Co., Ltd.
No. 2 Building, 3rd Floor and Room 410-412 4th Floor,
Shanghai International Holding Corp. GmbH (EUROPE)
Eiffelstrasse 80, 20537 Hamburg / Germany

www.microlife.com

Shanghai International Holding Corp. GmbH (EUROPE)

Eiffelstrasse 80, 20537 Hamburg / Germany

www.microlife.com

